



Superscope PMR61


United States & Canada



PMR61
Digital Audio
Recorder



Home



Play



Record



Record Check

| Recording | PMR61 |
|--|--------------------|
| Built-in 16GB Media (file settings for over 4300 Hrs of recording) | ✓ |
| Simultaneous Record to Internal Media & USB Flash Media | ✓ |
| Automatically Detects Input Sources & Internal Mics | ✓ |
| Record Check (Automatic Input Sensitivity, Attenuation, Record Level Settings) | ✓ |
| Flexible Sample Frequencies (44.1, 22.05, 11.025kHz) | ✓ |
| Flexible MP3 Bit Rates (320, 256, 160, 128, 64, 32, 16, 8 kbps) | ✓ |
| Active File Size Calculator (easy selection using recording parameters) | ✓ |
| Room Noise Low Cut Filtering (Normal or Maximum) | ✓ |
| Automatic Record Start (Power On and Audio Level Detect) | ✓ |
| One Touch Recording | ✓ |
| Add Company/Organization and/or Track Numbers to File Names Automatically | ✓ |
| Reduced File Size Recordings (email attachment friendly) | ✓ |
| 48V Phantom Power / 5 V for 1/8" Conference Mics | ✓ |
| Playback | PMR61 |
| Playback Formats (WAV & MP3) | ✓ |
| Recorded Files Automatically Named with Date/Time | ✓ |
| Convenient On-Screen Quick Search Forward and Back Playback Controls | ✓ |
| Move, Copy, Backup, and Delete Files | ✓ |
| Other | PMR61 |
| Large Color LCD Touch Screen Display (4.3" Diagonal) | ✓ |
| Instant Lookup for Inspecting PMR61 and File Properties | ✓ |
| PIN Password Secures Files and Protects PMR61 Settings | ✓ |
| Time Saving Features for Backing Up Files to Internal & USB Media | ✓ |
| Programmable Auto Delete Files (by date/time) | ✓ |
| USB Media Check (checks write speed of USB Media prior to recording) | ✓ |
| Battery Backup System (recording continues when AC is lost) | ✓ |
| Internal Battery Charging (Ni-MH AA Batteries x 4) | ✓ |
| Integrated Stand for Anti-Glare Viewing | ✓ |
| Lockable Theft Protection (laptop style) | ✓ |
| Auto Switching Professional Stereo Condenser Mics | ✓ |
| Built-In Speaker (mutes during recording to avoid feedback) | ✓ |
| Inputs / Outputs | PMR61 |
| USB 2.0 - Flash Drive Connection (Type A) | ✓ |
| USB 2.0 - Computer Connectivity (Micro USB) | ✓ |
| Balanced Mic / Line Input (XLR & 1/4" Combo x 2) | ✓ |
| Conference Mic Input (3.5mm x 2) | ✓ |
| Balanced Line Output (XLR x 2) | ✓ |
| Aux Input (RCA x 2) | ✓ |
| Line Output (RCA x 2) | ✓ |
| Headphone Output (1/4") with Volume Control | ✓ |
| Power Supply | PMR61 |
| Power Requirements (100V-240V, 50/60 Hz) | ✓ |
| Battery Operation Up To 5 Hrs (4 x AA Ni-MH Rechargeable / 2700 mAh) | ✓ |
| Battery Operation Up To 2.6 Hrs (4 x AA Alkaline / 1300 mAh) | ✓ |
| Accessories | PMR61 |
| AC Adapter | ✓ |
| USB Cable (Type A to Micro B) | ✓ |
| RCA Audio Cable | ✓ |
| User Guide (PDF on CD ROM) | ✓ |
| Dimensions | PMR61 |
| Size (inches) | 7.72 x 2.36 x 5.67 |
| Size (mm) | 196 x 60 x 144 |
| Weight (without batteries) | 2.3 lb |
| Weight (without batteries) | 1.04 kg |
| Shipping Weight | 5 lb |